

- SPECIFICATIONS
- Alternator Design Brushless
- Maximum Watts 6,000
- Continuous Watts 5,000
- Voltage 120/240V
- Maximum Amps @ 120V 50
- Continuous Amps @ 120V 41.6
- Maximum Amps @ 240V 25
- Continuous Amps @ 240V 20.8
- Frequency 60 Hz
- Phase Single
- Voltmeter Standard
- Full power switch Standard
- Main Circuit Breaker 21A
- Number of Poles (2-pole)
- Engine Manufacturer Honda
- Engine Model GX-340
- Horsepower (kW) 11.0 (8.25)
- Rated Speed-RPM 3,600
- Low Oil Shutdown Standard
- Starting Systems** Recoil
- Fuel Capacity-gal. (ltr) 5.0 (19)
- Running Time-hrs./tank*** 5.5
- Fuel Gauge Standard
- Automatic Idle Control Standard
- Sound Level @ 23 ft. 76dB
- Dimensions and Weight
- Length in. (cm) 25.6 (64)
- Width in. (cm) 22 (56)
- Height in. (cm) 21.3 (54)
- Dry Weight lbs. (kg) 194 (88)